

4A4D

The 4A4D interface supports a combination of four analog input/output channels and four digital PCM input/output channels. The analog channels are user-configurable with respect to input & output voltage level and impedance. Additionally, all four channels support independent sample rates from 10KSPS to 80 MSPS and DC input coupling. Each captured sample has 8 bits of resolution.

The digital PCM channels support bit-rates up to 52 Mbps and can be configured with respect to input & output clock phase, PCM code, signal level, randomize and de-randomization. Advanced features include, PCM packing format, PCM frame definition with frame lock indication.


The 4A4D interface also supports a monitor mode (E-to-E) in which the input signals are presented on the output connectors during RECORD and IDLE.



12D

The 12D interface board supports twelve digital PCM input/output channels. The digital PCM channels support bit-rates up to 40Mbps and can be configured with respect to input & output clock phase, PCM code, signal level, randomize and de-randomization. Advanced features include, PCM packing format, PCM frame definition with frame lock indication.

The 12D interface also supports a monitor mode (E-to-E) in which the input signals are presented on the output connectors during RECORD and IDLE.



2IF70, 140 & 370


The DRS-IFB-2IFxx supports two I/O channels for specific IF applications, with Input AGC to maintain constant signal levels for sampling. Input and output filters are tuned to specific Intermediate Frequency bands to provide superior signal capture and reproduction fidelity by removing any unwanted signals, such as harmonics and aliasing artifacts.

Additional digital filters are implemented on this interface with $\sin x/x$ correction for specific rates, which improves the flatness of the frequency response.



8E

The 8E interface board supports eight Ethernet input/output channels. The Ethernet channels can record all network traffic or custom filtered packets based on IP address and/or UDP port. During replay the Ethernet data is output as it was originally recorded or redirected to different destinations by IP address and/or UDP port. The replay output can also be filtered based on IP address and/or UDP port. Each channel can be configured for copper or optical I/O with COTS SFP modules.



2V-HD60

The 2V-HD60 interface supports two separate SD and HD-SDI video/audio record/playback channels using MPEG2 and MPEG4 H.264 compression.

Each channel supports both standard definition (SD) and high definition (HD). Analog/composite video is input/output for SD and digital SDI is used for HD. Video resolutions include NTSC 720 x 480, PAL 720 x 576, SDI 480i, 576i, 720 at

Interface Modules


TECHNICAL DESCRIPTION & SPECIFICATIONS

60fps and 1080 at 60fps. Each channel supports independent video bit rates from 1 to 12Mbps. Time overlay is also supported in both channels.


The 2V interface board supports a monitor mode (E-to-E) in which the video input signals are presented on the output connectors during record and while in IDLE.

ADDITIONAL BOARD OPTIONS


- 2CHAI:** Two Channel High Speed Analog Record and Replay
- 4E4S:** 4 Channel Ethernet & 4 Channel UART Record and Replay
- 4A4S:** 4 Channel Analog & 4 Channel UART Record and Replay
- 16A4D:** 16 Channel Analog & 4 Channel Digital PCM Record and Replay
- 4DBS:** 4 Channel Digital PCM with Bit Sync Record and Replay
- 12APM:** 12 Channel Power Monitor Record
- 16A:** 16 Channel Analog Record and Replay
- 16CAN:** 16 Channel Can Bus 2.0 Record and Replay
- 16M1553:** 8 Channel Dual Redundant 1553 Military Bus Record and Replay
- 2AR818:** 2 Channel ARINC 818 Avionics Bus Record and Replay
- 2E10G:** 2 Channel 10000 base T Ethernet Record and Replay
- 32AR429:** 32 Channel ARINC 429 Avionics Bus Record and Replay
- 64DISC:** 64 Channel Discrete Record and Replay
- 8AFDX:** 8 channel Avionics Full Duplex Ethernet Record and Replay
- 8AS5725A:** 8 Channel combined 1553 Military Bus and Discrete Record
- 8BCCDL:** 8 Channel Buffered Cross Channel Data Link Record
- 8FI394 (200B):** 8 Channel IEEE-1394 Firewire (200B) Record
- 8S:** 8 Channel UART Full & Half Duplex Record and Replay




4E4S




4A4S




12APM




16A




16CAN



16M1553



2AR818



64DISC

[Inquire today to learn more](#)

